

## DS-2FP2061 Indoor Security Microphone



- Support ceiling mounting, desktop mounting, and wall mounting
- Support centralized power supply, camera power supply, and DC power supply. Dedicated power supply is not required
- With high sensitivity and high fidelity, this microphone can pick up sounds which come from all directions, including a clear sound and high anti-disruption ability
- The built-in output driving circuit is able to directly drive earphones and other devices
- This device is suitable for pick up sounds within a close range. pickup range: up to 5 m, best pick up range: 3 m
- Support volume adjustment knob, which are used for adjusting volume according to surroundings.
- It is suitable for some practical situations like counter, cash register, meeting, negotiation, recording and so on
- There are built-in modules in the top of indoor pick-up, including power protection module, modules for protecting itself from lightning stroke and polarity reverse
- Innovative circuit design, clear content and high fidelity sound

## ▪ Specification

Microphone	
Type	electret
Polar Pattern	360° omni-directional
Pickup Range	0 m to 5 m
Frequency Response	20 Hz to 20 kHz
Sensitivity	-32 dB
SNR	90 dB
Sampling Rate	8 khz, 16 khz(default), 32 khz
Dynamic Range	0 dB to 90 dB
Function	
LED Indicator	Blue: Working normally
General	
Power	12 VDC , max. 0.1 W
Material	Plastic
Weight	Approx. 48 g (0.106 lb.)
Operating Condition	-10 °C to 50 °C (14 °F to 122°F) (indoor)
Dimension	Ø85 mm × 20.48 mm (Ø3.35" × 0.81")
Packing List	Device × 1 Regulatory Compliance and Safety Information × 1
Installation	Ceiling mounting, wall mounting, desktop mounting

## ▪ Available Model

DS-2FP2061

**Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
[www.hikvision.com](http://www.hikvision.com)



Follow us on social media to get the latest product and solution information.



Hikvision



HikvisionHQ



HikvisionHQ



Hikvision\_Global



Hikvision  
Corporate Channel



hikvisionhq